

Ancillary Generators

From 5kva to 200kva, we can provide generators for temporary power for small fans to 415v fan heaters, to large 30kw fans located in remote locations.



POWER	60 kva	80 kva	100kva	150kva	200kva
Bunded Fuel Tank	Yes	-	Yes	Yes	Yes
Fuel Consumption 100% load L per hr at 50Hz	14.77	21.5	26.5	34.96	45.99
Fuel Consumption 50% load L per hr at 50Hz	7.4	10.7	15.45	17.95	24.02
Fuel Consumption 75% load L per hr at 50Hz	11.27	15.9	22.5	25.92	34.95
Fuel Tank Capacity	390ltr	516ltr	516ltr	860ltr	860ltr
Generator Size kW	48	64	80	120	160
Height	1.82m	2m	2m	2.12m	2.12m
Length	2.54m	2.86m	2.86m	3.52m	3.52m
Width	1.15m	1.2m	1.19m	1.2m	1.2m
Phase Current Amps at 400V, 3 phase	87	115	144	216	289
Sound Pressure dBA at 1m	74	75	75	68	68
Sound Pressure dBA at 1m	63	64	64		
Weight Dry	1650kg	1990kg	2140kg	2800kg	2850kg
Weight Wet	1800kg	2580kg	2620kg		